

PTEL2R

APC Surge Module for Analog Phone Line, Replaceable, 1U, use with PRM4 or PRM24 Rackmount Chassis



Overview

Model Name	APC Surge Module for Analog Phone Line, Replaceable, 1U, use with PRM4 or PRM24 Rackmount Chassis
Includes	User Manual
Standard Lead Time	Usually in Stock
Product Distribution	Afghanistan , Albania , Algeria , Andorra , Angola , Anguilla , Antigua And Barbuda , Argentina , Armenia , Aruba , Australia , Austria , Azerbaijan , Bahamas , Bahrain , Bangladesh , Barbados , Belarus , Belgium , Belize , Benin , Bermuda , Bhutan , Bolivia , Bosnia And Herzegovina , Botswana , Brazil , Brunei Darussalam , Bulgaria , Burkina Faso , Burundi , Cambodia , Cameroon , Canada , Cayman Islands , Central African Republic , Chad , Chile , China , Colombia , Congo , CONGO, THE DEMOCRATIC REPUBLIC OF THE , Cook Islands , Costa Rica , <![CDATA[Cote D'Ivoire]]> , Croatia , Cuba , Cyprus , Czech Republic , Denmark , Djibouti , Dominica , Dominican Republic , East Timor , Ecuador , Egypt , El Salvador , Equatorial Guinea , Eritrea , Estonia , Ethiopia , Falkland Islands (Malvinas) , Fiji , Finland , France , Gabon , Gambia , Georgia , Germany , Ghana , Gibraltar , Greece , Grenada , Guadeloupe , Guatemala , Guinea , Guyana , French Guiana , Haiti , Honduras , Hong Kong , Hungary , Iceland , India , Indonesia , Iran (Islamic Republic Of) , Iraq , Ireland , Israel , Italy , Jamaica , Jordan , Kazakhstan , Kenya , KOREA, REPUBLIC OF , Kuwait , Latvia , Lebanon , Lesotho , Liberia , Liechtenstein , Lithuania , Luxembourg , Macedonia , Madagascar , Malawi , Malaysia , Mali , Malta , Martinique , Mauritania , Mauritius , Mexico , Moldova, Republic Of , Mongolia , Morocco , Mozambique , Myanmar , Namibia , Nepal , Netherlands , Netherlands Antilles , New Zealand , Nicaragua , Niger , Nigeria , Norway , Oman , Pakistan , Panama , Papua New Guinea , Paraguay , Peru , Philippines , Poland , Portugal , Puerto Rico , Romania , Russian Federation , Rwanda , SAINT KITTS AND NEVIS , SAINT LUCIA , SAINT VINCENT AND THE GRENADINES , Saudi Arabia , Senegal , Sierra Leone , Singapore , Slovakia (Slovak Republic) , Slovenia , Somalia , South Africa , Spain , Sri Lanka , Sudan , Suriname , Sweden , Switzerland , Taiwan , Tajikistan , TANZANIA, UNITED REPUBLIC OF , Thailand , Togo , Trinidad And Tobago , Tunisia , Turkmenistan , Turks And Caicos Islands , Uganda , Ukraine , United Arab Emirates , United States , Uruguay , Uzbekistan , Venezuela , Viet Nam , VIRGIN ISLANDS (UNITED STATES) , Western Sahara , Yemen , Zambia , Zimbabwe

Output

Number of Outlets	1
-------------------	---

Input

Input Power	0 W
Maximum Line Current per phase	0.0 A
Maximum Input Current	0 A

Surge Protection and Filtering

EMI/RFI Noise rejection (100 kHz to 10 MHz)	0.0 dB
Peak Current Normal Mode	0.2 kA
Peak Current Common Mode	0.25 kA
NM Surge Response Time (ns)	1.0 ns
Data Line Protection	Analog phone line for phone/fax/modem/DSL (RJ-45 connector)
Data Lines Protected(multi-line only)	Dual analog line (4 wire)
Let Through Voltage Rating	260

Physical

Net Weight	0.02 kg
Maximum Height	44.0 mm
Maximum Width	19.0 mm
Maximum Depth	69.0 mm
Shipping Weight	0.05 kg
Shipping Height	99.0 mm
Shipping Width	33.0 mm
Shipping Depth	95.0 mm
Master Carton Units	96.0
Master Carton Weight	14.77 lbs
SCC Codes	3073130420285 2
Color	Black
Units per Pallet	28.0

Environmental

Operating Environment	-15 - 45 °C
Operating Relative Humidity	0 - 95 %
Operating Elevation	0-3000 meters
Storage Temperature	-15 - 45 °C
Storage Relative Humidity	0 - 95 %
Storage Elevation	0-3000 meters

Conformance

Approvals	CE , UL 497A , cUL Recognized
Standard warranty	Lifetime

Sustainable Offer Status

RoHS	Compliant
Other Environmental Compliance	China RoHS